

PH 27

SERVICE PARTS DIAGRAM


Bulletin Date: Oct-17

Starting Serial Number:

VERSION A - D2015

TTI Model Number: 038 138 017







PH 27

SERVICE PARTS DIAGRAM


Bulletin Date: Oct-17

Starting Serial Number:

VERSION A - D2015

TTI Model Number: 038 138 017

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)





PH 27 SERVICE PARTS LIST

Bulletin Date: Oct-17

TTI Model Number: 038 138 017

Starting Serial Number:

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)

VERSION A - D201	5

ITEM	PART NUMBER	PART DISCRIPTION	QTY (PCS)
1	201739001	AUXILARY SIDE HANDLE ASSEMBLY	1
1a	620448002	DEPTH GAGE ROD	1
2	561993001	RUBBER CAP	1
3	-	CHUCK SLEEVE	1
4	-	C-RING	2
5	681154001	STEEL BALL	2
6	635043001	BALL PLATE	1
7	672799001	CONICAL SPRING	1
8	203443001	GEAR CASE ASSEMBLY	1
8d	635156001	LOCK PLATE	1
8e	692732001	LOCK PLATE SPRING	1
9	306972002	SHIFT KNOB ASSEMBLY	1
10	621637001	SDS SPINDLE	1
10a	692724004	BRAKE RING	1
10b	-	O-RING	1
10c	694882001	ANVIL SLEEVE	1
10d	-	O-RING	1
10e	-	O-RING	1
10f	694880001	ANVIL	1
10g	-	O-RING	1
10h	612244001	WASHER	1
10j	-	SNAP RING	1
10k	633517001	WASHER	1
10m	692735002	CLUTCH SPRING	1
10n	612126002	2ND STAGE GEAR	1
10p	612145002	CLUTCH PLATE	1
10q	611405001	STEEL BALL	3
10r	-	C-RING (THICKER THAN 10T)	1
10s	-	C-RING	1
11	635147001	WASHER	1
12	-	O-RING	1
12a	=	RAM	1
13	693984001	PISTON	1
14	ı	WASHER	2



SERVICE PARTS LIST

Bulletin Date: Oct-17

TTI Model Number: 038 138 017

Starting Serial Number: VERSION A - D2015

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)

15	ITEM	PART NUMBER	PART DISCRIPTION	QTY (PCS)
17 - GASKET 1 17a 642216002 DIAPHRAGM WITH BUSHING 1 17c - FELT PLUG 2 17d 902075002 SEAL RING 1 18 660165015 M4 X 10MM SCREW 2 19 203447001 110V ARMATURE ASSEMBLY 1 19a 681999001 BALL BEARING 1 19b 634848001 BEARING RETAINING PLATE 1 19c 298002024 ARMATURE 1 19d 661400001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 29 - C-RING 1 29 612129002 COUPLER 1 29 694889001 SHIFT SPRING 1 29 612128003 WOBBLE BEARING 1 29 612128003 WOBBLE BEARING 1 29 612128003 WOBBLE BEARING 1 29 612125001 BALL BEARING 1 30 203452001 HOUSING ASSEMBLY 1	15	692719001	WRIST PIN	1
17a 642216002 DIAPHRAGM WITH BUSHING 1 1 1 1 1 1 1 1 1	16	660436009	M4 X 35MM SCREW	4
17c	17	-	GASKET	1
17d 902075002 SEAL RING	17a	642216002	DIAPHRAGM WITH BUSHING	1
18 660165015 M4 X 10MM SCREW 2 19 203447001 110V ARMATURE ASSEMBLY 1 19a 681999001 BALL BEARING 1 19b 634848001 BEARING RETAINING PLATE 1 19c 298002024 ARMATURE 1 19d 681400001 BALL BEARING 1 20 66189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 66096002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29a 612130002 2ND STAGE PINION 1 29a 612127003 REDUCTION GEAR SHAFT 1	17c	-	FELT PLUG	2
19 203447001 110V ARMATURE ASSEMBLY 1 19a 681999001 BALL BEARING 1 19b 634848001 BEARING RETAINING PLATE 1 19c 298002024 ARMATURE 1 19d 681400001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 29 - C-RING 1 29 612127003 REDUCTION GEAR SHAFT 1 29c 612127003 REDUCTION GEAR SHAFT 1 29c 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 IST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1 1	17d	902075002	SEAL RING	1
19a 681999001 BALL BEARING 1 19b 634848001 BEARING RETAINING PLATE 1 19c 298002024 ARMATURE 1 19d 681400001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29a 612130002 2ND STAGE PINION 1 29a 612127003 REDUCTION GEAR SHAFT 1 29c 612128003 WOBBLE SCUPLER 1 29e 612128003 WOBBLE DUPLER 1 <t< td=""><td>18</td><td>660165015</td><td>M4 X 10MM SCREW</td><td>2</td></t<>	18	660165015	M4 X 10MM SCREW	2
19b 634848001 BEARING RETAINING PLATE 1 19c 298002024 ARMATURE 1 19d 681400001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - BRUSH SPRING 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 29 - C-RING 1 29 612130002 2ND STAGE PINION 1 29 612129003 REDUCTION GEAR SHAFT 1 29c 612128003 WOBBLE COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE BEARING 1 29h 635148001 RETAINING PLATE 1 29h 635148001 RETAINING PLATE 1 29h 635148001 RETAINING PLATE 1 29h 632452001 HOUSING ASSEMBLY 1 30 203452001 HOUSING ASSEMBLY 1	19	203447001	110V ARMATURE ASSEMBLY	1
19c 298002024 ARMATURE 1 19d 681400001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - BRUSH SPRING 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29d 694889001 SHIFT SPRING 1 29d 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1 30 203452001 HOUSING ASSEMBLY 1 31	19a	681999001	BALL BEARING	1
19d 68140001 BALL BEARING 1 20 661189001 M4 X 9MM SCREW 4 21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612128003 WOBBLE COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE BEARING 1 29f 681236008 WOBBLE BEARING 1 29h 635148001 RETAINING PLATE 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	19b	634848001	BEARING RETAINING PLATE	1
20 661189001 M4 X 9MM SCREW 21 527036001 FAN BAFFLE 22 203449001 110V FIELD ASSEMBLY 23 527909001 M0TOR HOUSING 24 303952005 BRUSH HOLDER 25 660960002 M3 X 8.5MM SCREW 26 - 110V CARBON BRUSH 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 29 - C-RING 29 - C-RING 30 612127003 REDUCTION GEAR SHAFT 41 10 10 10 10 10 10 10 10 10 10 10 10 10	19c	298002024	ARMATURE	1
21 527036001 FAN BAFFLE 1 22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 24a - BRUSH SPRING 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29a 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29k - <td< td=""><td>19d</td><td>681400001</td><td>BALL BEARING</td><td>1</td></td<>	19d	681400001	BALL BEARING	1
22 203449001 110V FIELD ASSEMBLY 1 23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 24a - BRUSH SPRING 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29k - M4 X 10MM SCREW 1 30 203452001	20	661189001	M4 X 9MM SCREW	4
23 527909001 MOTOR HOUSING 1 24 303952005 BRUSH HOLDER 2 24a - BRUSH SPRING 2 25 66096002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29h - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	21	527036001	FAN BAFFLE	1
24 303952005 BRUSH HOLDER 2 24a - BRUSH SPRING 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	22	203449001	110V FIELD ASSEMBLY	1
24a - BRUSH SPRING 2 25 660960002 M3 X 8.5MM SCREW 4 26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 6B1383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	23	527909001	MOTOR HOUSING	1
25 660960002 M3 X 8.5MM SCREW 26 - 110V CARBON BRUSH 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 1 29a 612130002 2ND STAGE PINION 1 1 29b 612127003 REDUCTION GEAR SHAFT 1 1 29c 612129002 COUPLER 1 1 29d 694889001 SHIFT SPRING 1 1 29e 612128003 WOBBLE COUPLER 29f 681236008 WOBBLE BEARING 1 1 29g 612125001 IST STAGE GEAR 1 1 29h 635148001 RETAINING PLATE 29j 681383001 BALL BEARING 1 1 29k - M4 X 10MM SCREW 1 1	24	303952005	BRUSH HOLDER	2
26 - 110V CARBON BRUSH 2 27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	24a	-	BRUSH SPRING	2
27 291167011 LEADWIRE ASSEMBLY-RED (NOT SHOWN) 1 28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 IST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	25	660960002	M3 X 8.5MM SCREW	4
28 291167012 LEADWIRE ASSEMBLY-BLACK (NOT SHOWN) 1 29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	26	-	110V CARBON BRUSH	2
29 - C-RING 1 29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	27	291167011	LEADWIRE ASSEMBLY-RED (NOT SHOWN)	1
29a 612130002 2ND STAGE PINION 1 29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	28	291167012	LEADWIRE ASSEMBLY-BLACK (NOT SHOWN)	1
29b 612127003 REDUCTION GEAR SHAFT 1 29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29	-	C-RING	1
29c 612129002 COUPLER 1 29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29 a	612130002	2ND STAGE PINION	1
29d 694889001 SHIFT SPRING 1 29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 IST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29b	612127003	REDUCTION GEAR SHAFT	1
29e 612128003 WOBBLE COUPLER 1 29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29c	612129002	COUPLER	1
29f 681236008 WOBBLE BEARING 1 29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29d	694889001	SHIFT SPRING	1
29g 612125001 1ST STAGE GEAR 1 29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29 e	612128003	WOBBLE COUPLER	1
29h 635148001 RETAINING PLATE 1 29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29f	681236008	WOBBLE BEARING	1
29j 681383001 BALL BEARING 1 29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29g	612125001	1ST STAGE GEAR	1
29k - M4 X 10MM SCREW 1 30 203452001 HOUSING ASSEMBLY 1	29h	635148001	RETAINING PLATE	1
30 203452001 HOUSING ASSEMBLY 1	29j	681383001	BALL BEARING	1
	29k	-	M4 X 10MM SCREW	1
30a 660024018 M4 X 16MM SCREW 6	30	203452001	HOUSING ASSEMBLY	1
	30a	660024018	M4 X 16MM SCREW	6



PH 27 SERVICE PARTS LIST

Bulletin Date: Oct-17


Starting Serial Number:

TTI Model Number: 038 138 017

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)

VERSION A - D2015

ITEM	PART NUMBER	PART DISCRIPTION	QTY (PCS)
30b	-	HOUSING HALVE - RIGHT	1
30d	•	HOUSING HALVE - LEFT	1
30e	902926001	FOAM PAD	2
31	760251036	230V SWITCH	1
32	661189001	CORD CLAMP	2
33	632823001	M4 X 9MM SCREW	1
34	730156015	POWER CORD - TAIWAN	1
34 a	-	STRAIN RELIEF	1
35	941046081	SERVICE NAMEPLATE	1
36	-	M5 X 8MM SCREW	2
40	302863008	BLOW MOLDED CARRYING CASE	1
41	203307001	BRUSH SERVICE KIT (SET OF 2)	1
42	525759001	COMMUTATOR INSULATOR	1
1000	203617002	BRUSH ASSY SERVICE PARTS KIT\ 038138\ ASIA	1
1200	-	TYPE Q2 GREASE 2.8oz/80g TUBE	1
1201	-	TYPE S2 GREASE 1.4oz/40g TUBE	2
2000	61-30-0290	SPINDLE SERVICE FIXTURE	1






SERVICE INSTRUCTION


Bulletin Date: Oct-17


Starting Serial Number:

VERSION A - D2015

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)












10 Spindle






Assembly of internal Spindle components:

- Lubricate Ram Catcher and O-Rings. Assemble O-Rings onto and into Ram Catcher. Assemble Anvil Assembly into Ram
- Catcher Assembly (large end into Ram Catcher as shown). Place the chamfered end of the Stop
- Washer over the small end of the Anvil.
 4. Place the assembled components
- from step 4 into the cavity of an old piston as shown. Use the old piston as an aid to push the assembled components deep into the Spindle cavity.
- C-Ring (10j) will be used to secure internal components inside the spindle. It is recommended to modify a flat blade screwdriver by filing or grinding a notch into the blade. Place the C-Ring upright as shown with the opening of the ring straight up. Use the modified screwdriver to push the C-Ring down into the Spindle cavity. Rotate the C-Ring in the spindle cavity as shown. Place the old piston into the Spindle cavity and tap the piston with a mallet to secure the C-Ring in the groove.





Assembly of external Spindle components:

Install Washer 10k and Spring 10m onto spindle. Lubricate and install the Clutch Gear 10n and Clutch Plate 10p onto the Spindle. Be sure to orient the part as shown and position with the three notches on the back of the plate over the holes in the spindle.

Place C-Ring 10r onto Spindle. (C-Ring 10r has a thicker cross section than C-Ring 10s.) With the aid of a snap ring pliers, work the C-Ring past the first spindle groove down to the other parts assembled onto spindle.

7. Place Spindle Service Fixture 61-30-0290 over the assembled parts and the Spindle. Position so the fixture rests on Clutch Plate 10p. Be sure the three notches are not covered. Place the fixture and spindle assembly in an arbor press and carefully compress the Clutch Spring enough to expose the three holes in the Spindle, As an aid, put a dab of grease on your finger to pick up and place the three Steel Balls 10q into the three small holes on the Spindle just above Clutch Plate. Ensure the notches in the Clutch Plate are aligned with the Steel Balls.

While compressed (a), use a screwdriver (b) to work C-Ring 10r into the Spindle groove. Ensure the Steel Balls are in place and slowly retract the arbor press. The Clutch Plate should slide over the Steel Balls until it is in contact with the C-Ring.

Place C-Ring 10s onto Spindle. With the aid of a snap ring pliers, work the C-Ring into the first spindle groove and snap into place.



SERVICE INSTRUCTION

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)


Bulletin Date: Oct-17

Starting Serial Number:

VERSION A - D2015

NOTE: C-Ring 10r is thicker than 10s 10s 10s in this groove 10g 10r in this groove 10p 10m

10k



Assembly of external Spindle components:

0

- Install Washer 10k and Spring 10m onto spindle. Lubricate and install the Clutch Gear 10n onto the Spindle 10. Be sure to orient the part as shown with the three flats on the Clutch Gear centered over the holes in the spindle.
- Place Spindle Service Fixture 61-30-0290 over the assembled parts and the Spindle. Position so the fixture rests on the Clutch Gear 10n. Be sure the three holes on the Spindle are not covered. Place the fixture and spindle assembly in an arbor press and carefully compress the Clutch Spring enough to expose the three holes in the Spindle.

As an aid, put a dab of grease on your finger to pick up and place the three steel balls 10q into the three small holes on the Spindle just above the Clutch Gear.


Remove the Spindle from the arbor press.

10. Lubricate and install the Clutch Plate 10p onto the Spindle. Be sure to orient the part such that three inside notches on the plate cover the Steel Balls in the Spindle. Place the C-Ring 10r onto the Spindle. (NOTE: C-Ring 10r has a thicker cross-section than C-Ring 10s). With the aid of a snap ring pliers, work the C-Ring past the first spindle groove, down to the other parts assembled onto the spindle.

Place Spindle Service Fixture 61-30-0290 over the assembled parts and the Spindle. Place the fixture and spindle assembly in an arbor press and carefully compress the Clutch Spring enough to expose the C-Ring groove in the Spindle.

While compressed, use a flat blade screwdriver to work C-Ring 10q into the spindle groove. Ensure that the Steel Balls are still in the spindle. Slowly retract the arbor press. The Clutch Plate should slide over the Steel Balls until it is in contact with the C-Ring.

With the aid of a snap ring pliers, work C-Ring 10s into top groove of Spindle.





SERVICE INSTRUCTION

Bulletin Date: Oct-17


Starting Serial Number:

VERSION A - D2015

TTI Model Number: 038 138 017

SDS-PLUS ROTARY HAMMER 26MM (3-MODE)

Black or Brown




From Red Field Lead 'A' to #8 on Switch

Red Leadwire Assembly 291167011 from LH Brush Holder to #5 on Switch



Blue Leadwire Assembly 291167012 from RH Brush Holder to #6 on Switch

From Black Field Lead 'D' to #7 on Switch



AS AN AID TO REASSEMBLY, TAKE NOTICE OF WIRE ROUTING AND POSITION IN WIRE GUIDES AND TRAPS WHILE DISMANTLING TOOL.

BE CAREFUL AND AVOID PINCHING WIRES BETWEEN HANDLE HALVES WHEN ASSEMBLING.

